



3 NODE SMART MODULE SERIES

#SwitchToSmart



DESCRIPTION

The 3 Node Module is a combination of Relay & Curtain Control. By Just adjusting the dip/toggle switches, one can easily customize its mode of operation to enable you to control:

- **EITHER** 1, 2 or all 3 of your relay switches (**ON/OFF**).
- **OR** your curtain/roller shades.



CONTROL ANY 3 ACTIONS



EASY INSTALLATION



RETROFIT DESIGN



ZWAVE COMPATIBILITY



APP CONTROL



VOICE CONTROL

SPECIFICATIONS


Model Number	HC-IM-3R-ZW-IN (Z-Wave) HC-IM-3R-WI-IN (Wi-Fi)
Power Requirement	AC 110-240V, 50-60Hz.
Dimensions	49.5x50.5x22 mm
Load Rating	Max 300w for resistive loads, 150w for Capacitive loads, 200w for inductive load
Operating Temperature	32°F - 104°F or 0°C - 40°C
Humidity	0-90%
Wireless Range	50m Outdoor - 20m Indoor
Radio Protocol	Available in both Z-Wave & Wi-Fi variants
Radio Signal Power	1m
Radio Frequency	EU - 868.40/869.40 MHz IN - 865.20 MHz BR/AU - 919.80/ 921.40 MHz US - 908.40/ 916/ 908.49 MHz
The Relay	Three
Curtain Control	One

PRE INSTALLATION MANDATORY CHECKS


- It is always advised to consult a certified electrician to perform the installation process.
- Ensure the Load capacity & Power requirements of your intended switch matches the technical specifications.
- Ensure you follow all national and local electrical codes for installation.
- **TURN OFF** the mains to make sure no power is running. You may check the same by using an inductive voltage detector.

INSTALLATION

Curtain Mode



Switch Mode



CONFIGURATION TO ZWAVE CONTROLLER

1. Set the controller into **inclusion** mode (Refer Controller's manual for instruction).
2. Press and hold the configuration button for **5 seconds**.
3. The **LED** starts blinking **BLUE**.
4. When the **BLUE** light holds steady, release the button.
5. On successful deletion of the device, the controller sends a confirmation message.

WARRANTY

Hogar Provides Limited Warranty of 18 months on every product

ENQUIRY

For Orders/Details, kindly reach out to us at info@hogarcontrols.com



Scan QR code for more details and Sales enquiries

