



INDOOR SIREN SMART SENSOR SERIES

#SmartSense



DESCRIPTION

The Indoor Siren connects with your existing Security or Safety System, via your Zigbee Gateway & Hogar SE App, and triggers an alarm in time to take the necessary precautions in case of a security breach.

As soon as an alarm sign is received by your security system, the Indoor Siren will sound a loud buzzer (>105 dB) and also flash a **RED** LED. The alarm volume, duration & flash can be adjusted through your Hogar SE App.



ALARM TRIGGER



ZIGBEE COMPATABILITY



EASY INSTALLATION



LINKAGE TO OTHER SMART DEVICES



APP CONTROL




VOICE CONTROL

SPECIFICATIONS

Model No.	HSE-SRN-001
Transmit Frequency	2.4000~2.4835 GHz
Working Voltage	5V DC Adapter
Dimensions	78 x 41 mm
Operating Temperature	-10° C - +55 °C
Humidity	0 - 95%
Wireless Protocol	ZigBee 3.0

PRE INSTALLATION MANDATORY CHECKS


- Ensure Indoor Siren is installed indoors ONLY.
- It is recommended that the indoor siren be installed either on the table or hung on the wall.



INSTALLATION

- Indoor Siren can be installed on your ceiling either by screwing it on or by using a 3M tape. Screw Installation is **ALWAYS** preferred.

SCREW MOUNTING



3M GLUE



ADDING INDOOR SIREN TO YOUR HOME

- Open the Hogar SE App and go to "Rooms".
- Click on "+" Button and select "Indoor Siren". Follow the prompts on your App for subsequent steps.
- Remove the bracket of your Indoor Siren by turning it **counterclockwise** & plug in the adapter DC plug to **TURN ON** the power source
- Slide the switch button to "ON" on the rear side.
- You will soon see the **RED LED** flash that indicates that the Indoor Siren has entered into **Enrolling Mode**.
- Press the **SET** Button for **5** seconds. It sends the request to the Zigbee Gateway.
- Click on "Confirm Indicator Rapidly Blink" on your Hogar SE App.

Reset the device first.

If the indicator is blinking fast, please skip the reset steps

- ⊖ Turn on the device
- ⊖ Hold RESET button (switch) for 5s. (please refer to the manual)
- ⊖ Confirm that the indicator is blinking fast

Attention: please complete pairing process within 3 minutes after device reset.



Confirm indicator rapidly blink

- Your Indoor Siren is now successfully added to your Hogar SE App.

WARRANTY

Hogar Provides Limited Warranty of 18 months on every product.

ENQUIRY

For Orders/Details, kindly reach out to us at info@hogarcontrols.com



Scan QR code for more details on warranty and sales enquiries